



23932

PATENT TRADEMARK OFFICE

CERTIFICATE OF MAILING BY EXPRESS MAIL

"EXPRESS MAIL" Mailing Label No: EL525017310US

Date of Deposit: January 18, 2001

I hereby certify that this paper or fee is being deposited with the U.S. Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231

Type or Print Name: Carol Mitchell

Carol Mitchell
Signature

IN THE UNITED STATES PATENT & TRADEMARK OFFICE

APPLICATION FOR PATENT

COMBINATION SWITCH AND ROUTING-SWITCHING
RADIO BASE STATION

INVENTOR

GUNNAR RODIN

COMBINATION SWITCH AND ROUTING-SWITCHING RADIO BASE STATION

REFERENCE TO RELATED APPLICATIONS

This application claims the benefit of priority from copending U.S. Provisional Application for Patent No. 60/177,805 titled "IP Packet Router Integrated into a Radio Base Station" filed on January 25, 2000, is related thereto, is commonly assigned therewith, and the subject matter thereof is incorporated herein by reference in its entirety.

BACKGROUND OF THE INVENTION

Technical Field of the Invention

The present invention relates in general to the telecommunications field and, in particular, to an apparatus providing both circuit-switched and packet-switched communications within a telecommunications network.

Description of Related Art

Radio base stations (RBSs) within a mobile telephony system are often used as

network traffic transmission transfer points to other base stations. Commonly used network topologies for connecting such base stations to each other include the chain, ring, and tree topologies. A single transmission link typically operates at rates of 2, 4, or 8 Mbit/second, which is greater than what is used by a single base station. Therefore, multiple base stations often use a single transmission link. Since the physical transmission medium is usually a radio link, base station sites often house radio link equipment as well.

Each base station is typically connected to the transmission network with one or more physical transmission links. The number of links depends on the desired network topology, requirements for redundancy, and the need for transmission capacity at the base station. In a circuit-switched network 9, an internal switch matrix is used to distribute fractions of connected bandwidth transmissions within the base station to various transceivers and other signaling devices. The built-in switch matrix is sometimes also used for switching excess bandwidth to another link in the transmission network. This link is then used for connection to other base stations. As shown in the prior art network block diagram of Figure 1A, a string of cascaded Internet nodes 20 and radio base stations 30 are connected via network ports 32 within a network 10, such as a combination Internet Protocol (IP) network 8 and a switching network 9. In the network 10 topology shown in Figure 1, circuit-switched (STM)

RBSs 30 are connected to Internet nodes 20. This type of mixed network 10 is a common migration scenario as users migrate from a completely circuit-switched network to an IP network. However, the flexibility provided by packet switched connections and the IP Suite in combination with circuit-switched networks requires a change in switching technology.

5 A converter 80 may be needed to convert signals between the circuit-switched network 9 and the IP network 8.

Each RBS 30 is typically controlled by a Base Station Controller (BSC) 40, and is connected to the controller 40 using a control/traffic port 31. For example, the BSC 40 keeps track of resources within the STM RBS 30. Such resources include the number and type of radio transceivers, and the number and type of internal switching connections. The connections within the switch 50 are known as "circuit-switched connections." The switch 50 setup (i.e., how time slots within a time frame 72 are switched) is accomplished using the BSC 40. Thus, it is the job of the BSC 40 to track resources within the base station, which include transceivers 60, 61 and connections within the switch 50. Once the connections within the switch 50 are set, they are usually not changed unless there is a disturbance within the transmission network 10 or the STM RBS 30 is shut down. The BSC 40 is also the source/destination for connections to from the RBS 30.

10

15

The transmission interface, such as a 2 Mbit/sec G.703 interface, delivers data in 32 byte frames 72, typically divided into one byte time slots 74. The switch 50 switches all time slots that have the same position in the frame 72 to one internal destination. For example, considering the circuit-switched transceivers 60, 61, the switch 50 may elect to send time slots #4 and #5, 76, 78, in each frame 72 to the transceiver 61 via internal interface connection 70.

The typical messages which are used to load IP networks include e-mail, file transfer, and accesses to the world-wide web. The length of these messages, which are divided into packets 82, is often a few hundred bytes, on up to a thousand or more bytes. For mobile radio systems, on the other hand, speech packets are typically used to load the network. These packets are quite small (i.e., on the order of 40-60 bytes) but are transmitted rapidly (i.e., about every 20 milliseconds. This disparity in packet size and frequency of transmission influences the optimal design and routing elements within a mixed network 10.

IP packets 82 from the nodes 20 can only be inserted into available time slots within the frames 72, which may require the use of a converter 80. Thus, IP-formatted information (i.e., packets 82) can be sent to the BSC 40 without changing the operational characteristics of the switch 50. In this way, IP-formatted data can be switched without routing, which is

inefficient.

As mentioned previously, the current solution is to divide the available bandwidth into small selected portions (i.e., one or more time slots) and assign them to each base station. However, when packet transmissions are used within the mixed network **10**, it is inefficient to divide the link bandwidth into fractions (i.e., one or more consecutive time slots) reserved to different base stations **30**. The bandwidth for each device or base station is thus reserved, and cannot be reused by other devices. Thus, the transfer time for individual packets will be fairly long if only a few time slots are used.

Thus, in mixed networks **10**, there is a need for efficient data distribution between RBSs **30** and the BSC **40**. This need is independent of the transmission network used. For migration from a circuit-switched network **9** to an IP network **8**, it should also be possible to mix IP routing and STM switching.

A related problem is illustrated in prior art figure 1B. Sending packet data **82** in an all-IP network **12** using conventional RBSs **30** requires an additional router **65**, which adds cost and requires space. Thus, a solution which obviates the need for the router **65** to communicate packet data to RBSs **30** in an all-IP network **12** is also needed.

SUMMARY OF THE INVENTION

In accord with one embodiment of the present invention, a combination switch includes a time slot switch and a router. The combination switch is in electronic communication with the telecommunications network providing frames of circuit-switched data and packets of IP data, such that the time slot switch receives the circuit-switched data, and the router receives the IP data. The router is in electronic communication with the time slot switch.

The combination switch may include one or more central processing units and one or more digital signal processors. Typically, the central processing unit communicates with the time slot switch and the router while executing one or more network management protocols, such as the Simple Network Management Protocol (SNMP). Typically, a digital signal processor is used to implement the time slot switch, and another digital signal processor is used to implement the router.

In another embodiment, the invention includes a routing-switching base station, which may be a radio base station, having a combination time slot switch and Internet Protocol switch (or separate time slot switch and router elements), in electronic communication with a plurality of transceivers. The base station is in electronic communication with a

telecommunications network providing frames of circuit-switched data and packets of IP data.
The combination switch receives the data, and sends it on to the plurality of transceivers.

In an alternative embodiment, a routing radio base station of the present invention includes a router for receiving one or more packets of IP data from the network, along with
5 a plurality of transceivers which are in electronic communication with the router. As the combination routing-switching base station migration solution is incorporated into networks over time, the need for the router and time slot switch combination is expected to give way to the router radio base station incorporating only the router.

BRIEF DESCRIPTION OF THE DRAWINGS

A more complete understanding of the method and apparatus of the present invention may be had by reference to the following detailed description when taken in conjunction with the accompanying drawings wherein:

FIGURES 1A and 1B, previously described, are prior art block diagrams of a mixed
15 network and all-IP network, respectively;

FIGURES 2A and 2B are block diagrams of the routing-switching base station and the routing radio base station, respectively, of the present invention; and

FIGURE 3 is a schematic block diagram of the combination switch of the present invention.

DETAILED DESCRIPTION OF THE DRAWINGS

5 The preferred embodiment of the present invention and its advantages are best understood by referring to Figures 1-3 of the drawings, like numerals being used for like and corresponding parts of the various drawings.

Turning now to Figure 2A, the routing-switching base station **100** of the present invention can be seen. Included within the base station **100**, which may be a radio base station, is a combination time slot switch and Internet Protocol switch **110**, which may
10 comprise a time slot switch **130** and a router **140**. Through a series of internal interface connections **70**, the combination switch **110** is placed into electronic communication with a plurality of transceivers **60, 90**. The transceivers may be radio frequency transceivers, optical transceivers, or other transceivers which operate using electromagnetic energy to
15 communicate information. Thus, when a network supplies frames **72** of circuit-switched data to the base station **100**, they may be received by the combination switch **110**, and selected portions of the frames **72** can be sent on to the transceivers **60**. Similarly, when packets **82**

are received from the network, the IP data packets **82** can be sent on to the transceivers **90**. The transceivers **60, 90** may be similar or identical. The numeric differentiation is (only) used to show that either transceiver **60, 90** may be used to send/receive frames **72** or selected packets **82** of data.

5 The combination switch **110** (or the individual elements of a time slot switch **130** and a router **140**) located in the routing-switching base station **100** is a network migration solution that lends itself to use in mixed networks having a combination of legacy equipment that operates only with circuit-switched data, and newer equipment that operates using packet-switched data. However, as time goes on, and the use of antiquated circuit-switched
10 equipment disappears, the routing-switching base station **100**, which may be a radio base station, will not require circuit switching functionality. The resulting routing radio base station **100'** will include the router **140** and one or more transceivers **90** in electronic communication with the router **140**, but not a time slot switch **130**. This solution, shown in Fig. 2B, solves the problem shown in Fig. 1B, wherein an extra router **65** is needed to
15 interface conventional RBSs **30** to the all-IP network **12**. In the invention, the equivalent of router **65**, i.e., router **140**, is now included within the routing radio base station **100'**.

Thus, a cost efficient solution is provided by the present invention to replace the

built-in switch matrix **50** of prior art base stations **30**. The new (replacement) combination switch **110** is capable of acting as a packet router, as a circuit switch, or as a device which can provide packet-switching and circuit-switching at the same time. The integrated device (i.e., switch) **110** is able to terminate traffic bound for the base station **100**, to forward traffic bound for other base stations, and to distribute traffic internally within the base station **100**. The router **140** within the switch **110** is programmed to understand and implement the IP Suite.

The switch **110** (or the router **140** alone) can be implemented using various logical building elements, and is not meant to be limited by the exemplary illustrations given herein. For example, as shown in Figure 3, the switch **110** can be implemented using a central processing unit **260** and one or more digital signal processing units **200**. Using such a combination of logical building elements provides several advantages. Central processing units have a flexible construction set and can address large amounts of memory. Thus, such central processing units are suitable to process programs that are not time critical, and require complex instruction sets. These units are relatively inexpensive, and it is possible to combine multiple central processing units in a cluster to achieve higher data processing rates.

On the other hand, Digital Signal Processors (DSPs) typically have a specialized

instruction set, and access less memory than that which can be accessed by a central processing unit. Thus, DSPs are suitable to process programs that are time critical, and require relatively unsophisticated program instructions. DSPs can also be clustered to provide increased throughput.

5 The various elements of the combination switch **110** can be grouped into integrated circuits, such as a first integrated circuit **250**, a second integrated circuit **260**, and a third integrated circuit **270**. Thus, in the exemplary implementation of the combination switch **110** shown in Figure 3, the first integrated circuit **250** may contain three DSPs **200** communicating with two memories **210**, an external interface **230**, and an internal interface **240** using a
10 common internal bus **255**. The bus **255** is also connected to the central processing unit **220**, located on the second integrated circuit **260**. The memory **210** within the third integrated circuit **270** is also connected to the bus **255**. Of course integrated circuits **250**, **260** and **270** can all be further integrated into a single circuit (not shown).

15 In the combination switch **110** configuration shown in Figure 3, the circuitry within the second integrated circuit **260** (i.e., the central processing unit **220**) can communicate using Direct Memory Access (DMA) with the DSPs **200** and the memories **210** located in the first integrated circuit **250**. Another bus (not shown in Figure 3) may be used for DSP **200**

instruction fetches from the memories **210**, or other memories (not shown). The integrated circuit **250** may also contain special hardware and/or firmware for High-level Data Link Control (HDLC) protocol conversion. In the exemplary configuration of Figure 3, the time slot switch **130** ¹¹⁰ may be implemented using the interfaces **230**, **240**, the memories **210**, and programs in two of the three DSPs **200**. The remaining DSP **200** (and excess capacity of the other DSPs **200**) and the central processing unit **220** and the DSPs **200** are used to execute the IP Instruction Suite. Some of the routines needed for transferring a message through the combination switch **110**, and executed within the DSPs **200**, might include HDLC controls, Point-to-Point Protocol (PPP), Link Control Protocol/Neighbor Discovery Protocol (LCP/NDP) for initiating PPP, multilink PPP, header compression, queuing (e.g., quality of service) and policing algorithms, packet forwarding IP, and the User Datagram Protocol (UDP). Typically, the memory **210** necessary for storing programs executed in the DSPs **200**, along with the memory **210** needed for a data storage, will be a few hundred kilobytes. The DSPs should operate at a program execution speed of approximately one billion instructions per second (i.e., 1,000 Mips).

In the central processing unit **220**, several protocols are required for setup, supervision, exception handling, etc. These include: IP Options Part, IP fragmentation, Open

Shortest Path First (OSPF) routing protocol, and the Simple Network Management Protocol (SNMP). The memory **210** required by the central processing unit **220** should be on the order of several megabytes. The operating speed of the central processing unit will typically be about several million instructions per second (e.g., 1-10 Mips).

5 The routing-switching base station **100**, the routing radio base station **100'**, and the combination switch **110** allow implementation of inexpensive router functionality in the place of conventional radio base stations, which contain only circuit-switching operational elements. Such an implementation allows use of the combination switch as a general IP packet router at little or no additional cost.

10 The combination switch **110** can be used as an internal packet switch so that packets from different devices can share the entire bandwidth allowed. Thus, the combination switch **110** can use a portion of the bandwidth for the base station **100** for circuit switched data **72**, and another portion of the bandwidth for packet-switched data **82**. Using an internal router **140** for switching will provide faster packet transfer speeds and shorter queuing delays for
15 high priority packets when priority mechanisms are used.

The combination switch **110** configuration also allows internal devices, such as transceivers **60, 90**, to be addressed as IP nodes, and if desired, to be visible to the external network **10**. Using a router **140** as an internal switching device operating under the IP Suite means that special, non-standard protocols, will not be needed to operate the switch **110**.

5 Additional advantages of the switch **110** include automatic routing updates when the surrounding network **10** is changed (e.g., using the OSPF protocol); increased possibilities for plug-and-play base stations connected to a routing-switching base station **100**; standardized supervision methods, operation, and maintenance (e.g., using the SNMP protocol); and standardized methods for verifying quality of service, policing, and resource
10 allocation.

During migration operations, there will be the opportunity for connecting routing-switching base stations where circuit-switch connections are required. As noted above, in this case, circuit-switched data can use some fraction of the bandwidth, while IP routed data can use the remaining fraction of the bandwidth. Conversion routines from the
15 IP and circuit-switch formats can be implemented using the combination switch **110** for direct interfacing to transceivers **60, 90**. The functionality of the switch **110**, implemented as described above, can now be changed using software so that the switch **110** can act as a time

slot switch **130** alone, a combination switch **130**, or a router **140** alone, and manual visits to the site of the switch **110** to change its function are obviated. Also, as noted above, the routing radio base station **100'** (see Fig. 2B) may only require the presence of a router **140** and transceivers **90** when circuit-switched data is no longer present in the network **10**.

5 Finally, the DSPs **200** can operate as high performance packet switches, or as high performance circuit-switches. Circuit-switching and packet-switching can also be accomplished simultaneously. The same DSP **200** can perform internal distribution of data to various transceivers **60**, **90** and other signaling devices. The DSPs **200** can also be assigned responsibility for internal data conversion (i.e., from circuit-switching protocols to
10 IP, and vice versa). The DSPs **200** can also handle data routing and buffering, and administer Quality-of-Service functions within the IP Suite. The router **140** can also be used to concentrate several links that are lightly loaded into a single link for better utilization of available bandwidth.

 Although a preferred embodiment of the method and apparatus of the present

invention has been illustrated in the accompanying drawings and described in the foregoing detailed description, it will be understood that the invention is not limited to the embodiment disclosed, but is capable of numerous rearrangements, modifications and substitutions without departing from the scope of the invention as set forth and defined by the following claims.

17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227